## **DatasheetArchive.**com

#### **Request For Quotation**

Order the parts you need from our real-time inventory database. Simply complete a request for quotation form with your part information and a sales representative will respond to you with price and availability.

**Request For Quotation** 

Your free datasheet starts on the next page.

More datasheets and data books are available from our homepage: http://www.datasheetarchive.com



2.9 3.6

(Unit : mm)

# IS1U621/IS1U621L

#### Features

- 1. Compact
  - (Volume : About 1/8 compared with GP1U58X)
- 2. High sensitivity (Ultimate distance : MIN. 8 m)
- 3. B.P.F. (Band Pass Frequency) center frequency : (TYP. 38kHz)



#### Recommended Operating Conditions

| Paranueter               | Symbol | Recommended<br>operating conditions | Unit |
|--------------------------|--------|-------------------------------------|------|
| Operating supply voltage | Vcc    | 4.7 to 5.3                          | V    |

1 In the absence of confirmation by device specification sheets, SHARP takes no responsibility for any defects that occur in equipment using any of SHARP's devices, shown in catalogs, data books, etc. Contact SHARP in order to obtain the latest version of the device specification sheets before using any SHARP's device."

### Sensors for Remote Control

3.5 3.5

3.4 3.4

Outline Dimensions

IS1U621

#### Electrical Characteristics

| Electrical Characteristics  |                 |                                      |                       | (T     | $a=25^{\circ}C, V$ | cc =+5V) |
|-----------------------------|-----------------|--------------------------------------|-----------------------|--------|--------------------|----------|
| Parameter                   | Symbol          | Conditions                           | MIN.                  | TYP.   | MAX.               | Unit     |
| Dissipation current         | Icc             | No input light, Output terminal OPEN | -                     | 2.8    | 4.5                | \mA∨     |
| High level output voltage   | V <sub>OH</sub> | *3, Output terminal OPEN             | V <sub>CC</sub> - 0.2 | -      | -                  | V        |
| Low level output voltage    | V OL            | *3, *4                               | -                     | 0.45   | 0.6                | > v      |
| High level pulse width      | T1              | *2                                   | 400                   | (-(    | 800                | μs       |
| Low level pulse width       | T2              | *3                                   | 400                   | -      | 800/               | μs       |
| B.P.F. center frequency     | fo              | -                                    |                       | 38     |                    | kHz      |
| *5 Linear ultimate distance | L               | Ee < 10 lx                           | 8,0                   | $\sim$ | -                  | m        |
|                             |                 |                                      |                       |        |                    |          |

\*3 The burst wave as shown in the following figure shall be transmitted.

\*4 Pull-up resistance :  $2.2k\Omega$ 

\*5 By SHARP transmitter



#### SHARP

#### IS1U621/IS1U621L

#### Performance

Using the transmitter shown in Fig. 1, the output signal of the light detecting unit is good enough to meet the following items in the standard optical system in Fig. X.

(1) Linear reception distance characteristics

When L=0.2 to 8 m, Ee < 10 lx (\*6) and  $\phi = 0^{\circ}$  in Fig. 2, the output signal shall meet the electrical characteristics in the attached list (2) Sensitivity angle reception distance characteristics

When L=0.2 to 5 m, Ee < 10 lx ( \*6) and  $\phi$ <= 30  $^{\circ}$   $\,$  in the direction X and  $\,\theta\,$  =0  $^{\circ}$   $\,$  in the direction Y in Fig. 2,

the output signal shall meet the electrical characteristics in the attached list. Further, the electrical characteristics shall be net

when L=0.2 to 5 m, Ee < 10 lx (\*6) and  $\phi = 0^{\circ}$  in the direction X and  $\theta \le 15^{\circ}$  in the direction Y.

\*6 It refers to detector face illuminance.



In the above figure, the transmitter should be set so that the output Vout can be  $40mV_{P-P}$ .

However, the **PD49PI** to be used here should be of the short-circuit current  $I_{SC}$  =2.6  $\mu$  A at Ev=100 lx.

(Ev is an illuminance by CIE standard light source A (tungsten lamp),)





#### Fig. 6 Spectral Sensitivity for Reference



#### Precautions for Operation

- (1) Use the light emitting unit (remote control transmitter), in consideration of performance, characteristics, operating conditions of light emitting device and the characteristics of the light detecting unit.
- (2) Pay attention to a malfunction of the light detecting unit when the surface is stained/with dust and refuse.

Care must be taken not to touch the light detector surface.

- Conduct cleaning as follows.
- (3) Cleaning

Solvent dip cleaning : Solvent temperature of 45 °C max., dipping time : Within 3 minutes

Ultrasonic cleaning : Elements are affected differently depending on the size of cleaning bath, ultrasonic output, time,

size of PWB and mounting method of elements.

Conduct trial cleaning on actual operating conditions in advance to make sure that no problem results.

• Use the following solvents only.

Solvents: Ethyl alcohol, methyl alcohol or isopropyl alcohol

- (4) To avoid the electrostatic breakdown of IC, handle the unit under the condition of grounding with human body, soldering iron, etc.
- (5) Do not apply unnecessary force to the terminal.
- (6) Example of recommended external circuit (mount outer mounting parts near the sensor as much as possible.)

