

Request For Quotation

Order the parts you need from our real-time inventory database. Simply complete a request for quotation form with your part information and a sales representative will respond to you with price and availability.

[Request For Quotation](#)

Your free datasheet starts on the next page.


More datasheets and data books are available from our homepage: <http://www.datasheetarchive.com>

Sensors Hermetic Optoschmitts

Hermetically sealed optoschmitts are available in TO-18 and TO-46 metal-can packages, with different pinouts. They are graded on input sensitivity with radiant intensity maximum ranging from 2.5 mW/cm² (SD5600-001, SD5620-001) to 0.13mW/cm² (SDXX4-003). The devices are tested using a monochromatic IRED operating at 935nm.

These devices consist of a photodiode, linear amplifier, Schmitt trigger, and an output stage. Device polarity is determined in the output stage. For that reason, all electrical specifications are listed together and followed by an output cross-reference to allow proper choice for output configuration and polarity.

SD5004, SD5014, SD5304, SD5314, SD5604 and SD5614

Package Style	Parameter	min.	max.	units	Test Conditions
	Supply Voltage	4.5	16.0	V	SD5304, 5314, 5604 and 5614
		4.5	7.0	V	SD5004, 5014
	Supply Current		15.0	mA	V _{cc} = 16V, H = 0 to 10 mW/cm ²
	Output Saturation Voltage		0.4	V	I _{OL} = 12.8mA, V _{cc} = 5.5V
	Radiant Threshold				
	-301		1.50	mW/cm ²	V _{cc} = 5.0V
	-302		0.25	mW/cm ²	V _{cc} = 5.0V
	-303		0.13	mW/cm ²	V _{cc} = 5.0V
	Hysteresis (Note 1)	33	67	%	V _{cc} = 5.0V
	Propagation Delay				
	LO to HI, HI to LO		5.0	μs	V _{cc} = 5.0V, R _L = 390Ω (totem-pole, 8TTL loads)
	Rise Time		70	ns	same as propagation delay
	Fall Time		70	ns	same as propagation delay

Drawing 26
Page 42

SD5600, SD5610, SD5620 and SD5630

Package Style	Parameter	min.	max.	units	Test Conditions
	Supply Voltage	4.5	16.0	V	
	Supply Current		12.0	mA	V _{cc} = 5.0V, H = 0
	Supply Current		15.0	mA	V _{cc} = 16.0V, H = 0
	Output Saturation Voltage		0.4	V	I _{OL} = 12.8 mA, V _{cc} = 5.0V
	Radiation Threshold				
	SD5600-1, SD5610-1		2.5	mW/cm ²	V _{cc} = 5.0V
	SD5620-1, SD5630-1		0.25	mW/cm ²	V _{cc} = 5.0V
	SD5620-2, SD5630-2		0.13	mW/cm ²	V _{cc} = 5.0V
	Hysteresis (Note 1)	5.0	30.0	%	V _{cc} = 5.0
	Propagation Delay				
	LO to HI, HI to LO		5.0	μs	R _L = 390Ω, C _L = 50pf
	Rise Time		150.0	ns	same as propagation delay
	Fall Time		15.0	ns	same as propagation delay

Drawing 27
Page 42

OUTPUT CROSS REFERENCE

Part Number(s)	Polarity	Output Definition	Output Type
SD5004	buffer	LO with H = 0	totem-pole
SD5014	inverter	HI with H = 0	totem-pole
SD5304	buffer	LO with H = 0	open-collector
SD5314	inverter	HI with H = 0	open-collector
SD5604, 5600, 5620	buffer	LO with H = 0	10KΩ pull-up to V _{cc}
SD5614, 5610, 5630	inverter	HI with H = 0	10KΩ pull-up to V _{cc}

NOTE 1: Hysteresis is defined as the difference between the operating and release threshold intensities, expressed as a percentage of the operate threshold intensity.

Plastic Encapsulated Optoschmitts Sensors

Plastic encapsulated optoschmitts are available in two side-looking packages; pinouts are identical, but lead spacing and forming are different. They are graded on input sensitivity with radiant intensity maximum ranging from 2.5 mW/cm² to 0.37mW/cm². The devices are tested using a monochromatic IRED operating at 935nm.

These devices consist of a photodiode, linear amplifier, Schmitt trigger, and an output stage. Device polarity is determined in the output stage. For that reason, all electrical specifications are listed together and followed by an output cross-reference to allow proper choice for output configuration and polarity.

SDP8004, SDP8014, SDP8304, SDP8314, SDP8604, and SDP8614

Package Style	Parameter	min.	max.	units	Test Conditions
	Supply Voltage	4.5	5.5	V	SDP8004, SDP8014
	Supply Voltage	4.5	16.0	V	SDP8304, 8314, 8604, 8614
	Supply Current		15.0	mA	V _{CC} = 16V, H = 0 to 10mW/cm ²
	Output Saturation Voltage		0.4	V	I _{OL} = 12.8mA, V _{CC} = 5.5V
	Radiant Threshold				
	-301	.08	.37	mW/cm ²	V _{CC} = 5.0V
	Hysteresis (Note 1)	33	67	%	V _{CC} = 5.0V
	Propagation Delay				
	LO to HI, HI to LO		5.0	μs	V _{CC} = 5.0V, R _L = 390Ω (totem-pole, 8TTL loads)
	Rise Time		70	ns	same as propagation delay
Drawing 28 Page 42	Fall Time		70	ns	same as propagation delay

SDP8600, SDP8601, SDP8602, SDP8610, SDP8611, and SDP8612

Package Style	Parameter	min.	max.	units	Test Conditions
	Supply Voltage	4.5	16.0	V	
	Supply Current		12.0	mA	V _{CC} = 5.0V, H = 0
	Supply Current		15.0	mA	V _{CC} = 16.0V, H = 0
	Output Saturation Voltage		0.4	V	I _{OL} = 12.8mA, V _{CC} = 5.0V
	Radiant Threshold				
	-1		2.5	mW/cm ²	V _{CC} = 5.0V
	-2		1.2	mW/cm ²	V _{CC} = 5.0V
	-3		0.6	mW/cm ²	V _{CC} = 5.0V
	Hysteresis (Note 1)	5.0	30.0	%	V _{CC} = 5.0V
	Propagation Delay				
Drawing 29 Page 42	LO to HI, HI to LO		5.0	μs	R _L = 390Ω, C _L = 50pf
	Rise Time		150.0	ns	same as propagation delay
	Fall Time		15.0	ns	same as propagation delay

OUTPUT CROSS REFERENCE

Part Number(s)	Polarity	Output Definition	Output Type
SDP8004	buffer	LO with H = 0	totem-pole
SDP8014	inverter	HI with H = 0	totem-pole
SDP8304	buffer	LO with H = 0	open-collector
SDP8314	inverter	HI with H = 0	open-collector
SDP8600, 8601, 8602	buffer	LO with H = 0	10KΩ pull-up to V _{CC}
SDP8604	buffer	LO with H = 0	10KΩ pull-up to V _{CC}
SDP8610, 8611, 8612	inverter	HI with H = 0	10KΩ pull-up to V _{CC}
SDP8614	inverter	HI with H = 0	10KΩ pull-up to V _{CC}

NOTE 1: Hysteresis is defined as the difference between the operating and release threshold intensities, expressed as a percentage of the operate threshold intensity.