



產品搜尋:

[首頁](#)[English](#)[繁體中文](#)[日本語](#)[網站導覽](#)[公司簡介](#)[產品資訊](#)[公關新聞](#)[技術支援](#)[投資訊息](#)[聯絡方式](#)[人才招募](#)**HOT !**[智慧型輸出入控制](#)[系統單晶片](#)[數位多媒體應用](#)[機電整合](#)[產品資訊](#) >> [機電整合](#) >> **PT30DFx**

PT30DFx

DC BRUSHLESS MOTOR DRIVER IC: Single-Phase Full-Wave Linear Drive

OVERVIEW

The PT30DFx is single-phase full-wave driver IC. This driver IC can be used for single coil DC brushless motor. This driver IC accepts the hall IC's output signal and drives the motor coil directly without any other extra transistors. This IC can be operated from 2V to 18V supply voltage and driving current can be up to 400mA.

FEATURE

Applications

- Single coils DC brushless motor
- DC 2.0V~18V
- PT-30DFA FG Output
- PT-30DFT/B RD Output

Features

- Single-phase full-wave linear driver
- Switch noise elimination
- Motor lock protection and automatic restart
- Connectable direct to Hall element
- Built-in hysteresis comparator
- Frequency Generation output (PT-30DFA)
- Rotate Detection output (PT-30DFT/B)
- Low Power consumption and high driving efficiency

Input Devices

- Hall IC or Hall Element




PACKAGE & MARKING: SOP8 / MSOP8



SOP 8 L

PT-30DFT



MSOP-8

DFX
x=A:PT-30DFA
x=B:PT-30DFB

SPECIFICATIONS**Absolute Maximum Ratings (Ta = 25C)**

Parameter	Symbol	Conditions	Ratings	Units
Maximum supply voltage	V_{DD}^{max}		18	V
Allowable power dissipation	P_d		450[*]	mW
Operating temperature	Ta		-30 ~ +100	°C
Storage temperature	Ts		-55 ~ +150	°C
Output Continuous current	I_{out}	Max.	350	mA
Output Peak current	I_{out}	$T \leq 20\mu s$	450	mA

*On 50mm x 50mm x 1.6mm glass epoxy board

[Top](#) 

Copyright© 2003 Prolific Technology Inc. All Right Reserved